

## Design Of C-Shape Slot Microstrip Patch Antenna With Line Feed For WLAN Technology

K.Chandra Sekhararao<sup>1</sup>, Ch.Babu<sup>2</sup>

<sup>1</sup>(Electronics and Communication Engineering, Sasi Institute of Technology & Engineering, India)

<sup>2</sup>(Electronics and Communication Engineering, Sasi Institute of Technology & Engineering, India)

---

**Abstract:** Microstrip patch antenna becomes very popular day-by-day because of its ease of analysis and fabrication, low cost, light weight, easy to feed and their attractive radiation characteristics. To overcome the drawbacks of patch antenna, various feeding techniques have proposed. We propose a new simple design based on line feed technique and the dielectric constant used is Teflon. In this paper we are inserting a C-Shape and H-Shape slot on rectangular patch to compare the impedance bandwidth and gain. After simulation, the obtained results for C-Shape slot on rectangular patch have impedance bandwidth 4% and gain as 4.8 db at 4.5GHz. The proposed antenna is suitable for WLAN technology.

**Keywords:** Microstrip; Bandwidth; Dielectric constant; Line feeding; Return Loss

---

### I. Introduction

Wireless communications have progressed very rapidly in recent years, and many mobile units are becoming smaller and smaller. It started with hand gestures, then sounds produced by vocal chords and gradually me moved to wired communication and now wireless communication. In wireless communication we mainly exploit the Electromagnetic Spectrum. To meet the miniaturization requirement, the antennas employed in mobile terminals must have their dimensions reduced accordingly. Planar antennas, such as micro strip and printed antennas have the attractive features of low profile, small size, and conformability to mounting hosts. For this reason, compact, broadband and wideband design technique for planar antennas have been attracted much attention from antenna researchers.[8] Very recently, especially after the year 2000, many novel planar antenna designs to satisfy specific bandwidth specifications of present day mobile cellular communication systems have been developed. Planar antennas are also very attractive for applications in communication devices for wireless local area network (WLAN) systems in the 2.4 GHz (2400 – 2484 MHz) and 5.2 GHz (5150 – 5350 MHz) bands.[11]

The major need for today's communication devices is to operate at broader band such as to support high speed internet, multimedia communication and similarly many more broadband services, this is achieved by using microstrip patch antennas, but inherently microstrip antennas are narrow band antennas so, various techniques are used to enhance the bandwidth of microstrip antenna[2]. The excitation of microstrip antenna can have many configurations like microstrip line, coaxial, aperture coupling and proximity coupling. Out of these microstrip line and the coaxial feeds are easy to fabricate. By using coaxial probe feed technique produces low spurious radiation but narrow bandwidth [3]. To increase the speed of access and number of users with less crosstalk and interference data rates and bandwidth have to be increased for a particular operating frequency. By using different feeding techniques available and by inserting different slots on patch improves return loss, gain and radiation pattern [1] [4]. So in this paper we are using H-Shape and C-Shape slot on fractal patch on the Ground plane is used to reduce the size of antenna [7]. Return loss is a measure of how well devices or lines are matched. This discontinuity can be a mismatch with the terminating load or with a device inserted in the line. Return loss is related to both standing wave ratio (SWR) and reflection coefficient ( $\Gamma$ ). Increasing return loss corresponds to lower SWR. A match is good if the return loss is high. A high return loss is desirable and results in a lower insertion loss [5][6].

### II. Design Specifications

Based on the simplified formulation that has been described, a design procedure is outlined which leads to practical designs of rectangular micro strip antennas. The procedure assumes that the specified information includes the dielectric constant of the substrate ( $\epsilon_r$ ), the resonant frequency ( $f_r$ ), and the height of the substrate h.[10]

- Dielectric constant ( $\epsilon_r$ )  
i.e.,  $2.2 \leq \epsilon_r \leq 12$  [2]
- Operating frequency ( $f_0$ ) = 1.85 to 5 GHz
- Height (h)  
i.e.,  $0.003\lambda_0 \leq h \leq 0.05\lambda_0$

Where  $\lambda_0$ =free space wavelength

- Width of the microstrip patch antenna,

$$w = \frac{1}{(2 * fr \sqrt{\mu_o \epsilon_o})} \sqrt{\left(\frac{2}{\epsilon_r + 1}\right)}$$

Where, c = velocity of light

$f_r$  = operating frequency

$\epsilon_r$  = substrate dielectric constant

Generally practical width,  $w < \lambda_0$

- Effective dielectric constant

$$\epsilon_{eff} = \frac{\epsilon_r + 1}{2} + \frac{\epsilon_r - 1}{2} * \frac{1}{\sqrt{(1 + 12h/w)}}$$

- Length of the patch,

$$L = L_{eff} - 2\Delta L$$

Where

$$L_{eff} = \frac{c}{2f_o \sqrt{\epsilon_r}} \quad \text{and}$$

$$\Delta L = 0.412h \frac{(\epsilon_{eff} + 0.300) \left(\frac{w}{h} + 0.264\right)}{(\epsilon_{eff} - 0.258) \left(\frac{w}{h} + 0.800\right)}$$

For practical length ,  $0.3333 \lambda_0 < L < 0.5 \lambda_0$  [1]

### III. Calculation of Parameters

In this session we consider three frequencies and calculations are done.

**Assuming Operating frequency , ( $f_0$ ) = 4.5 GHz**

Dielectric constant as TEFLON

For Teflon dielectric constant( $\epsilon_r$ )=2.2

**Calculation of width:**

$$w = \frac{1}{(2 * fr \sqrt{\mu_o \epsilon_o})} \sqrt{\left(\frac{2}{\epsilon_r + 1}\right)}$$

W= 26.3 mm

Practical width ,  $w < \lambda_0$

i.e., 0.0263mm < 0.066mm

**Calculation of height:**

Height (h) =  $0.003\lambda_0 \leq h \leq 0.05 \lambda_0$

$\lambda_0 = c / f_0$

$$\lambda_0 = \frac{3 * 10^8}{4.5G} = 0.066 \text{ mm}$$

0.198 mm  $\leq h \leq$  3.3 mm

Assuming height = 0.8 mm which is in between 0.198 and 3.3 mm

**Calculating Effective Dielectric Constant:**

$$\epsilon_{eff} = \frac{\epsilon_r + 1}{2} + \frac{\epsilon_r - 1}{2} * \frac{1}{\sqrt{(1 + 12h/w)}}$$

$\epsilon_{eff} = 2.11$

**Calculating length:**

We know that ,  $L_{eff} = L + 2\Delta L$

$$\rightarrow L = L_{eff} - 2\Delta L$$

$$L_{eff} = \frac{c}{2f_o \sqrt{\epsilon_{eff}}}$$

$L_{eff} = 22.9 \text{ mm}$

$$\Delta L = 0.412h \frac{(\epsilon_{eff} + 0.300) \left(\frac{w}{h} + 0.264\right)}{(\epsilon_{eff} - 0.258) \left(\frac{w}{h} + 0.800\right)}$$

$\Delta L = 0.422 \text{ mm}$

$$L = L_{eff} - 2\Delta L = 22.4 \text{ mm}$$

For practical length

$0.3333 \lambda_0 < L < 0.5 \lambda_0$

$0.3333(0.066) < L < 0.5(0.066)$

$21.9 \text{ mm} < L < 33 \text{ mm}$

**Ground Plane Dimensions:**

Length of the ground plane ( $L_g$ ) =  $2L = 44.94 \text{ mm}$

Width of the ground plane ( $W_g$ ) =  $2W = 52.6$  mm

**Assuming Operating frequency ( $f_0$ ) = 2.6GHZ,**

Dielectric constant as TEFLON

For Teflon dielectric constant( $\epsilon_r$ )=2.2

**Calculation of width:**

$$w = \frac{1}{(2 * fr \sqrt{\mu_o \epsilon_o})} \sqrt{\left(\frac{2}{\epsilon_r + 1}\right)}$$

$W = 0.046m$

$W = 46mm$

Practical width  $w < \lambda_0$

$0.046 < 0.115$

**Calculation of height:**

Height ( $h$ ) =  $0.003 \lambda_0 \leq h \leq 0.05 \lambda_0$

$\lambda_0 = c / f_0$

$\lambda_0 = 0.115$

$0.115 \leq h \leq 5.7mm$

Assuiming height = 1.5mm which is in between 0.115and 5.7mm

**Calculating Effective Dielectric Constant:**

$$\epsilon_{eff} = \frac{\epsilon_r + 1}{2} + \frac{\epsilon_r - 1}{2} * \frac{1}{\sqrt{(1 + 12h/w)}}$$

$\epsilon_{eff} = 1.7803$

**calculating length:**

we know that ,

$$L_{eff} = L + 2\Delta L$$

→  $L = L_{eff} - 2\Delta L$

$$L_{eff} = \frac{c}{2f_0 \sqrt{\epsilon_{eff}}}$$

$L_{eff} = 43mm$

$$\Delta L = 0.412h \frac{(\epsilon_{eff} + 0.300) \left(\frac{w}{h}\right)^{0.264}}{(\epsilon_{eff} - 0.258) \left(\frac{w}{h}\right) + 0.800}$$

$\Delta L = 0.83014267mm$

$L = L_{eff} - 2\Delta L$

$L = 41.33mm$

For practical length

$0.3333 \lambda_0 < L < 0.5 \lambda_0$

$38.3 < L < 57.5$

**Assuming Operating frequency ( $f_0$ ) = 2.1GHZ**

Dielectric constant as TEFLON

For Teflon dielectric constant( $\epsilon_r$ ) = 2.2

**Calculation of width:**

$$w = \frac{1}{(2 * fr \sqrt{\mu_o \epsilon_o})} \sqrt{\left(\frac{2}{\epsilon_r + 1}\right)}$$

$W = 0.0564m$

$W = 56.4mm$

Practical width  $w < \lambda_0$

$0.0564 < 0.115$

**Calculation of height:**

Height ( $h$ ) =  $0.003 \lambda_0 \leq h \leq 0.05 \lambda_0$

$\lambda_0 = c / f_0$

$\lambda_0 = 0.142$

$0.4 \leq h \leq 7.1mm$

Assuiming height = 2.8mm which is in between 0.4 and 7.1mm

**Calculating Effective Dielectric Constant:**

$$\epsilon_{eff} = \frac{\epsilon_r + 1}{2} + \frac{\epsilon_r - 1}{2} * \frac{1}{\sqrt{(1 + 12h/w)}}$$

$\epsilon_{eff} = 2.07$

**Calculating length:**

we know that ,

$$L_{eff} = L + 2\Delta L$$

→  $L = L_{eff} - 2\Delta L$

$$L_{\text{eff}} = \frac{c}{2f_0\sqrt{\epsilon_{\text{eff}}}}$$

$$L_{\text{eff}} = 49.6\text{mm}$$

$$\Delta L = 0.412h \frac{(\epsilon_{\text{eff}} + 0.300)\left(\frac{W}{h} + 0.264\right)}{(\epsilon_{\text{eff}} - 0.258)\left(\frac{W}{h} + 0.800\right)}$$

$$\Delta L = 1.4\text{mm}$$

$$L = L_{\text{eff}} - 2\Delta L$$

$$L = 46.8\text{mm}$$

For practical length

$$0.3333 \lambda_0 < L < 0.5 \lambda_0$$

$$0.046 < L < 0.07$$


**Table 1:** Comparison of Antenna Parameters for Different Frequencies

Frequency (f <sub>0</sub> )	Teflon (ε <sub>r</sub> )	Height of the Substrate (h)	Width of the Patch (W)	Length of the Patch (L)	Width of the Ground Plane (W <sub>g</sub> )	Length of the Ground Plane (L <sub>g</sub> )
4.5GHz	2.2	0.8mm	26.3mm	61mm	52.6mm	44.94mm
2.1GHZ	2.2	2.8mm	56.4mm	46.8mm	73.2mm	63.6mm
2.6GHZ	2.2	1.5mm	46mm	41.3mm	55mm	50.3mm


From table we consider 4.5GHz frequency.

#### IV. Outline of Patch Antenna At 4.5 Ghz

The outline of patch antenna at 4.5 GHz is shown in the fig. 1.



**Figure 1:** Patch antenna dimensions at 4.5 GHz




**Figure 2:** Patch antenna dimensions at 4.5 GHz

Results regarding the performance of patch antenna and comparison of parameters with C and H- Shape slots on patch designed at an operating frequency of 4.5 GHz

#### V. Results

The below outputs represents the plots of C-shape slot on patch antenna with line feed. **S-parameters (S11) Vs Frequency plot:**



**Figure 3 :** S-parameters (S11) Vs Frequency plot

Here the Patch antenna is simulated at operating frequency of 4.5GHz. The S11 value at -10db is return loss.

**Return loss = -21.50**

**Impedance Bandwidth:**

The difference between upper and lower-cut off frequencies at S11 value -10db from the above graph is taken as bandwidth.

$$\text{Bandwidth}(\%) = (4.49 \text{ GHz} - 4.31 \text{ GHz}) / 4.5\text{GHz}$$

Impedance Bandwidth = 4 %

**Directivity:**

The directivity obtained for the designed micro strip line feed patch antenna is obtained as  $D(\theta, \phi) = 5.2 \text{ db}$  (as  $W < \lambda$ )

The plot of directivity at different angles of  $\theta$  is as follows.




Figure 4 : Polar plot for directivity




Figure 5 : Rectangular plot for directivity

**Radiation Efficiency:**

Radiation efficiency obtained for this design is 0.92465 .

**Gain:**

Antenna Gain in a particular direction is equal to the Directivity in that direction multiplied by the Antenna Efficiency.

$$G(\theta, \phi) = E * D(\theta, \phi)$$

**G (□, □) = 4.8 db**

The plot of gain at different angles of  $\theta$  is as shown below.




Figure 6 : Polar plot for gain





Figure 7: Rectangular plot for gain

**VSWR Vs Frequency Plot:**




**Figure 8: VSWR Vs Frequency Plot**

VSWR obtained from the above graph is 1.

**VSWR = 1**


**Radiation Pattern:**

The 2-D far field pattern obtained for 4.5GHz is as shown below.



**Figure 9: Polar plot for radiation pattern**

3-D far field pattern is shown below.



**Figure 10: 3-D Radiation pattern**

**Table 2:** Comparison of Output Parameters at Different Frequencies for H-slot

FREQUENCY (GHz)	RETURN LOSS (db)	BANDWIDTH (MHz)	DIRECTIVITY (db)	GAIN (db)	VSWR
4.5	-22.7	70	5.2	4.7	1
2.6	-19	60	5.2	4.6	1
2.1	-18	50	5.2	4.7	0.8

The table 3 shows comparison of antenna output parameters at frequency 4.5 GHz with C-Shape and H-Shape slots on patch.

**Table 3:** Comparison of Output parameters at 4.5 GHz for C and H-shape slots

PARAMETER	C-Shape slot	H-Shape slot
Return loss (db)	-21.5	-22.7
Band width (%)	4.5	1.5
Gain (db)	4.8	4.7
Directivity (db)	5.2	5.2
VSWR	1	1

From the table 3 simulation results the patch designed with C-Shape slot produces more bandwidth and gain.

## VI. Conclusion And Future Scope

### Conclusion:

In this paper we designed patch antenna operating at 4.5 GHz and compared the results for C and H-Shape slots. We can say that there are many aspects that affect the performance of the antenna such as dimensions, selection of the substrate, feed technique and also the Operating frequency can take their position in effecting the performance. From the above table we conclude that the design with C-Shape slot provides more bandwidth and gain compared to H-Shape slot results.

### Future Scope

It is very important to take the feed technique, the impedance and the substrate as main parameters into consideration. The proper position to terminate the Feed line also affects the performance of the antenna. In future other different type of feed techniques can be used to calculate the overall performance of the antenna without missing the optimized parameters in the action.

## Acknowledgements

We express our deep sense of gratitude to the Management of Sasi Institute of Technology and Engineering, Tadepalligudem, for providing us with an opportunity to fulfill our most cherished desire of reaching my goal. We would like to take this opportunity to thank our beloved Principal Dr. K Bhanu Prasad and Mr. N Venkat Rao, Academic Dean for providing a great support for completing our work. We extremely thankful to Mr. N V G Prasad, Head of the Department, Electronics and Communication Engineering, Sasi Institute of Technology and Engineering, Tadepalligudem, for the imponderable guidelines he has given during the research work.

## References

- [1] Raied A. R. Ibrahim, Mustapha C.E. Yagoub, "Practical Novel Design Component of Microstrip Patch Slot Antenna MSPSA for RFID applications", *Institute of Electrical and Electronics Engineers (IEEE)*, 2010.
- [2] Kashwan K R, Rajeshkumar V, Gunasekaran T and Shankar Kumar K R, "Design and Characterization of Pin Fed Microstrip Patch Antenna", *Institute of Electrical and Electronics Engineers (IEEE)*, Eighth International Conference on Fuzzy Systems and Knowledge Discovery (FSKD), 2011
- [3] Mohammed N. Shakib, M. Moghavvemi, and Wan N. L. Mahadi, "A Low Profile Patch Antenna for Ultrawideband Application", *IEEE*, 2015.
- [4] Mamta Devi, Sharma Abhishek, Katariya Dr. R. S. Meena, "E Shaped Patch Microstrip Antenna for WLAN Application Using Probe Feed and Aperture Feed" *IEEE, International Conference on Communication Systems and Network Technologies*, 2012.
- [5] T.V. Padmavathy, M. Dinesh Kumar and L. Joy Jason, "Design of quad slot microstrip patch antenna with edge feed for wimax applications", *IEEE, Chennai Fourth International Conference on Sustainable Energy and Intelligent Systems*, Dec 2013.
- [6] Sanjeev dwivedi, Abhishek Rawat, R.N.Yadav, "Design of u-shape microstrip patch antenna for wimax applications at 2.5 ghz", *IEEE*, 2013.
- [7] Mehre-eMunir, Ahsan Altaf, Muhammad Hasnain, "Miniaturization of microstrip fractal h-shape patch antenna using stack configuration for wireless applications", *IEEE 2nd International Conference on Recent Trends in Information Systems (ReTIS)*, 2015.
- [8] C. A. Balanis, *Antenna theory analysis and design*, John Wiley and Sons, New York, 1996, 2nd edition.
- [9] John D Kraus, Ronald J Marhefka, Ahmad S Khan, "Antennas and Wave Propagation", McGraw Hill Education (India) Private Limited; Fourth edition (April 5, 2010).
- [10] K D Prasad, "Antenna and Wave Propagation", Publisher: Satya Prakashan, 2012.
- [11] Operating Frequencies of Mobile Communications, <http://www.izmf.de/en/what-frequency-ranges-are-used-mobile-communications>